



# Standard Practice for Obtaining Colorimetric Data from a Visual Display Unit Using Tristimulus Colorimeters<sup>1</sup>

This standard is issued under the fixed designation E1455; the number immediately following the designation indicates the year of original adoption or, in the case of revision, the year of last revision. A number in parentheses indicates the year of last reapproval. A superscript epsilon ( $\epsilon$ ) indicates an editorial change since the last revision or reapproval.

## INTRODUCTION

This practice provides directions for correcting the results obtained with tristimulus colorimeters when measuring the tristimulus values or chromaticity coordinates of colored displays. Tristimulus colorimeters approximate the CIE color matching functions  $\bar{x}(\lambda)$ ,  $\bar{y}(\lambda)$ ,  $\bar{z}(\lambda)$  to make these measurements. The errors generated in measuring colors on a display may be minimized using this practice.

### 1. Scope

1.1 This practice is intended as an aid for improving the accuracy of colorimetric measurements made with tristimulus colorimeters on visual display units, such as cathode ray tubes (CRTs) and self-luminous flat-panel displays. It explains a useful step in the analysis of colorimetric data that takes advantage of the fact that light from such displays consists of an additive mixture of three primary colored lights. However, it is not a complete specification of how such measurements should be made.

1.2 This practice is limited to display devices and colorimetric instruments that meet linearity criteria as defined in the practice. It is not concerned with effects that might cause measurement bias such as temporal or geometric differences between the instrument being optimized and the instrument used for reference.

1.3 *This standard does not purport to address all of the safety concerns, if any, associated with its use. It is the responsibility of the user of this standard to establish appropriate safety and health practices and determine the applicability of regulatory limitations prior to use.*

### 2. Referenced Documents

2.1 *ASTM Standards:*<sup>2</sup>

**E284 Terminology of Appearance**

**E1336 Test Method for Obtaining Colorimetric Data From a Visual Display Unit by Spectroradiometry**

**E1341 Practice for Obtaining Spectroradiometric Data from Radiant Sources for Colorimetry**

2.2 *ISO/CIE Standard:*

**CIE Standard Colorimetric Observers, ISO/CIE 10527: 1991 (E)** (International Organization for Standardization, Geneva, 1991)<sup>3</sup>

### 3. Terminology

3.1 *Definitions:* Unless otherwise stated, definitions of appearance terms in Terminology **E284** are applicable to this practice.

3.2 *Definitions of Terms Specific to This Standard:*

3.2.1 *calibration, n*—in reference to a tristimulus colorimeter, the process performed outside of this practice to adjust the tristimulus colorimeter to provide the best possible results for average or predefined conditions.

3.2.2 *optimization, n*—in reference to a tristimulus colorimeter, the process performed pursuant to this practice to adjust the tristimulus colorimeter or to interpret its readings to provide better results when applied to a particular display device.

3.2.3 *compatible, adj*—in reference to a tristimulus colorimeter, one so designed as to automate the procedure described in this practice.

### 4. Summary of Practice

4.1 Tristimulus colorimeters comprised of three or four detector channels are, in general, not amenable to accurate

<sup>1</sup> This practice is under the jurisdiction of ASTM Committee **E12** on Color and Appearance and is the direct responsibility of Subcommittee **E12.06** on Image Based Color Measurement.

Current edition approved March 1, 2010. Published March 2010. Originally approved in 1992. Last previous edition approved in 2003 as E1455 – 03. DOI: 10.1520/E1455-03R10.

<sup>2</sup> For referenced ASTM standards, visit the ASTM website, [www.astm.org](http://www.astm.org), or contact ASTM Customer Service at [service@astm.org](mailto:service@astm.org). For *Annual Book of ASTM Standards* volume information, refer to the standard's Document Summary page on the ASTM website.

<sup>3</sup> Currently available through the U.S. National Committee of the CIE, c/o Mr. Thomas M. Lemons, TLA-Lighting Consultants, Inc., 7 Pond Street, Salem, MA 01970-4819. Also included in *ASTM Standards on Color and Appearance*, Fifth Edition, 1996.

calibration that holds for all manner of usage with different illuminated devices and objects. This is because the spectral responsivities of their detector channels do not exactly match the defined Commission Internationale de L'Éclairage (CIE)  $\bar{x}(\lambda)$ ,  $\bar{y}(\lambda)$ ,  $\bar{z}(\lambda)$  functions. Factory or subsequent calibration reflects judgments and compromises that may not be readily apparent. Nevertheless, this practice provides guidance on how such a tristimulus colorimeter may be optimized for use with a particular video display device, providing better accuracy with that device than its more general calibration provides. An optimization matrix transforms the instrumental (measured) CIE  $X$ ,  $Y$ ,  $Z$  values into adjusted  $X$ ,  $Y$ ,  $Z$  values that are closer to the ideal. This matrix is determined by reference to a colorimeter with higher intrinsic accuracy. The method derives from the fact that the color stimulus functions from display devices are linear combinations of three primary functions and are not entirely arbitrary.

## 5. Significance and Use

5.1 This practice may be applied when tristimulus colorimeters are used to measure the colors produced on self-luminous video display devices such as CRTs and flat-panel displays, including electroluminescent (EL) panels, field emission displays (FEDs), and back-lit liquid crystal displays (LCDs). This practice is not meant to be a complete description of a procedure to measure the color coordinates of a display. Rather, it provides a method for obtaining more accurate results when certain conditions are met. It may be used by any person engaged in the measurement of color on display devices who has access to the requisite equipment.

5.2 This practice defines a class of tristimulus colorimeters that may be said to be compatible with this practice.

## 6. Background of Practice

### 6.1 Colorimetry:

6.1.1 Color measurement instruments consist, in general, of means to measure radiometric power as transmitted through a number of bandpass filters. Most commonly, electrical devices are used to measure the filtered light. They may be used with different filters in succession, or multiple devices may be used concurrently. In instruments called spectroradiometers, the radiometric power is measured through a large number (typically 30 to 500) of narrowband filters. (Practice E1341 describes how a monochromator or polychromator (spectrograph) may be employed to filter and measure light in separate bands on the order of 1-nm wide.) In instruments called tristimulus colorimeters, the radiometric power is measured through three or four wideband filters. These filters may be constructed from dispersive elements (prisms and gratings) or from materials with selective spectral transmission or reflection. The latter may be either uniform or comprised of different patches, in a mosaic pattern, that provide the desired overall effect.

6.1.2 No matter how many filters are used, or in what manner, the goal of the measurement process is to determine tristimulus values  $X$ ,  $Y$ ,  $Z$ , as defined by ISO in its Standard

10527 and the CIE in its publication No. 15.2 (1).<sup>4</sup> For light with a color stimulus function  $\Phi(\lambda)$ ,

$$X = k \int_{360 \text{ nm}}^{830 \text{ nm}} \Phi(\lambda) \bar{x}(\lambda) d\lambda \quad (1)$$

$$Y = k \int_{360 \text{ nm}}^{830 \text{ nm}} \Phi(\lambda) \bar{y}(\lambda) d\lambda \quad (1)$$

$$Z = k \int_{360 \text{ nm}}^{830 \text{ nm}} \Phi(\lambda) \bar{z}(\lambda) d\lambda \quad (1)$$

where:

$k$  is 683 lm/W for emissive devices, such as displays, and  $\bar{x}(\lambda)$ ,  $\bar{y}(\lambda)$ ,  $\bar{z}(\lambda)$  are color-matching functions. While the standard definition of  $X$ ,  $Y$ ,  $Z$  requires the use of the CIE 1931 2° color-matching functions, the mathematics described in this practice would also be applicable to any other set of color-matching functions, such as the CIE 1964 10° functions.

6.1.3 In practice, color measurement instruments compute  $X$ ,  $Y$ ,  $Z$  by the summation of the signals as measured through the various filters, each signal being multiplied by an appropriate calibration factor. In matrix notation:

$$\begin{bmatrix} X_m \\ Y_m \\ Z_m \end{bmatrix} = \begin{bmatrix} C_{X1} & C_{X2} & C_{X3} & \dots & C_{Xf} \\ C_{Y1} & C_{Y2} & C_{Y3} & \dots & C_{Yf} \\ C_{Z1} & C_{Z2} & C_{Z3} & \dots & C_{Zf} \end{bmatrix} \begin{bmatrix} F_1 \\ F_2 \\ F_3 \\ \vdots \\ F_f \end{bmatrix} \quad (2)$$

where:

$F_1$ ,  $F_2$ ,  $F_3$ , through  $F_f$  are the electrical signals from the  $f$  filtered detectors and the  $C_{ij}$  are calibration coefficients.  $X_m$ ,  $Y_m$ ,  $Z_m$  have subscripts to indicate that they are measured values rather than ideal ones.

6.1.4 In this practice, we presume that the color measuring instrument is linear: that each signal  $F_a$  is strictly proportional to the received optical power, that any zero-offset (background in darkness) is removed, that the proportionality for signal  $F_a$  is not affected by the value of signal  $F_b$ , and in the case of closely packed detectors (such as charge-coupled device (CCD) detector elements) no signal  $F_a$  spills over and affects signal  $F_b$  as it approaches saturation. These presumptions are amenable to experimental verification using methods beyond the scope of this practice (2).

6.1.5 The values of the matrix elements  $C_{ij}$  may be determined using criteria that depends on the design and intended application of the instrument. The full extent of this subject is beyond the scope of this practice. However, in general, for spectroradiometers ( $f \approx 30$  to 500),  $C_{Xj}$  reflects the tabulated value of  $\bar{x}(\lambda)$  near the center wavelength of Filter  $j$  as well as the spectral responsivity of the corresponding detector channel. (Likewise,  $C_{Yj}$  and  $C_{Zj}$  reflect  $\bar{y}(\lambda)$  and  $\bar{z}(\lambda)$ , respectively.) For tristimulus colorimeters, the choice of  $C_{ij}$  is discussed further, below. As a general matter, the instrument designer should choose passbands and matrix elements that balance accuracy, sensitivity, and other design requirements.

6.1.6 Tristimulus colorimeters are generally designed with filters that are intended to match the spectral responsivities of

<sup>4</sup> The boldface numbers in parentheses refer to the list of references at the end of this standard.

their detector channels to the CIE  $\bar{x}(\lambda)$ ,  $\bar{y}(\lambda)$ ,  $\bar{z}(\lambda)$  functions. For such an instrument,

$$\begin{bmatrix} X_m \\ Y_m \\ Z_m \end{bmatrix} = \begin{bmatrix} C_{X1} & 0 & 0 \\ 0 & C_{Y2} & 0 \\ 0 & 0 & C_{Z3} \end{bmatrix} \begin{bmatrix} F_1 \\ F_2 \\ F_3 \end{bmatrix} \quad (3)$$

where:

the non-zero  $C_{ij}$  matrix elements represent adjustable gains of the detector channels. However, the  $\bar{x}(\lambda)$  function has two distinct lobes. This may be dealt with by splitting  $\bar{x}(\lambda)$  into  $\bar{x}_{\text{short}}(\lambda)$  and  $\bar{x}_{\text{long}}(\lambda)$ , each with a separate filter ( $F_1$  and  $F_2$ , respectively). For such an instrument,

$$\begin{bmatrix} X_m \\ Y_m \\ Z_m \end{bmatrix} = \begin{bmatrix} C_{X1} & C_{X2} & 0 & 0 \\ 0 & 0 & C_{Y3} & 0 \\ 0 & 0 & 0 & C_{Z4} \end{bmatrix} \begin{bmatrix} F_1 \\ F_2 \\ F_3 \\ F_4 \end{bmatrix} \quad (4)$$

Alternatively, the  $\bar{z}(\lambda)$  function may serve the role of  $\bar{x}_{\text{short}}(\lambda)$  since they have a similar shape,

$$\begin{bmatrix} X_m \\ Y_m \\ Z_m \end{bmatrix} = \begin{bmatrix} C_{X1} & 0 & C_{X3} \\ 0 & C_{Y2} & 0 \\ 0 & 0 & C_{Z3} \end{bmatrix} \begin{bmatrix} F_1 \\ F_2 \\ F_3 \end{bmatrix} \quad (5)$$

In all of these cases, it is difficult to realize an exact match between the CIE color-matching functions and the actual spectral responsivities of the corresponding detector channels. This means that no choice of  $C_{ij}$  will provide perfect calibration for all applications of the instrument. The criteria for setting the  $C_{ij}$  might not be well documented for a particular instrument.

6.1.7 It is generally believed that spectroradiometers, with their many detector channels, may be calibrated to yield superior measurements of  $X$ ,  $Y$ ,  $Z$  for diverse applications. Nevertheless, the relative simplicity of tristimulus colorimeters and their commensurately lower cost have made them popular where the highest accuracy is not required.

## 6.2 Self-Luminous Displays:

6.2.1 A self-luminous display, such as a CRT, an electroluminescent (EL) panel, a field emission display (FED), or a back-lit liquid crystal display (LCD) generates colored light by the proportional superposition (addition) of primary colored lights  $\Phi_r(\lambda)$ ,  $\Phi_g(\lambda)$ ,  $\Phi_b(\lambda)$ . The subscripts represent red, green, and blue, the primary colors of an additive set. An arbitrarily colored patch on the visual display has one and only one color stimulus function  $\Phi(\lambda)$ ,

$$\Phi(\lambda) = a\Phi_r(\lambda) + b\Phi_g(\lambda) + c\Phi_b(\lambda) \quad (6)$$

where  $a$ ,  $b$ ,  $c$  are coefficients that are determined by the display electronics.

6.2.2 The display electronics vary  $a$ ,  $b$ ,  $c$  over the face of the display in order to generate a colored image. For this practice, we presume that the display electronics may be set to make  $a$ ,  $b$ ,  $c$  uniform (perhaps after averaging nonobvious fine-structure) over a sufficient area of the display to permit measurements to be made on that area.

6.2.3 It is a requirement for the applicability of this practice that the display device behaves as stated in Eq 6. This practice does not represent that any particular display device will act as predicted by Eq 6, though those within the mentioned classes of devices might do so. The procedure for experimental verification of this property for a specific display device is beyond the scope of this practice (3).

## 6.3 Colorimetric Measurement of Displays:

6.3.1 Each of the primary color stimulus functions  $\Phi_r(\lambda)$ ,  $\Phi_g(\lambda)$ ,  $\Phi_b(\lambda)$  stimulates responses in the  $f$  detector channels that may be represented by a vector  $F$  (that is,  $F_r$ ,  $F_g$ ,  $F_b$ ). Given their construction, these vectors are linearly independent. (None of the three can be expressed as a linear combination of the other two.) While  $F$  is an element of an  $f$ -dimensional vector space, it is clear that only a three-dimensional subspace is spanned by the  $F$ 's of all possible color stimulus functions following Eq 6. Further, the mapping of  $F$  into  $(X_m, Y_m, Z_m)$  space by Eq 2 remains three dimensional. In other words, there is a one-to-one mapping of the vector  $(a, b, c)$  onto  $(X, Y, Z)$  by application of Eq 1; and, for a particular instrument with a fixed calibration matrix  $C$ , there is also a one-to-one mapping of the vector  $(a, b, c)$  onto  $(X_m, Y_m, Z_m)$ . From this we deduce that a matrix  $R$  exists that can be used to translate  $(X_m, Y_m, Z_m)$  values into actual  $(X, Y, Z)$  values.

6.3.2 A colorimeter that takes advantage of this fact must provide means for implementing the matrix  $R$ . That is, all  $f$  filtered detector signals should contribute linearly toward the computation of each output,  $X_m$ ,  $Y_m$ ,  $Z_m$ , instead of using different detectors for each output. This idea was reported as long ago as 1973 by Wagner (4), and it has been expanded upon and rediscovered by others since then (5-10).

6.3.3 On the basis of this property, a tristimulus colorimeter can be optimized for use on a self-luminous display by the proper derivation of a matrix  $R$  for that display. We proceed on the assumptions that the components are sufficiently stable, and that similarly built displays have similar enough spectral primaries to make a derivation of  $R$  worthwhile. However, these assumptions should be quantified before accuracy claims are made in any specific situation.

6.3.4 On the basis of this property, a tristimulus colorimeter designed for use with displays need not produce signals  $F$  that are close to CIE tristimulus values. Signal/noise may be improved by matching the spectral responsivities of the filtered detectors to the emission spectra of the primary colors. In such designs, it is especially important to use a matrix  $R$  that is specific to the particular  $\Phi_r(\lambda)$ ,  $\Phi_g(\lambda)$ ,  $\Phi_b(\lambda)$ .

## 7. Optimization

### 7.1 General:

7.1.1 Given the existence of a matrix  $R$ , how is it determined? Experimentally, the problem is one of comparing the data  $X, Y, Z$  from a reference colorimeter with the data  $X_m, Y_m, Z_m$  from the colorimeter being optimized, for a number of color samples at different display settings. From these data,  $R$  is calculated.

7.1.2 This practice is not directly concerned with the absolute accuracy of the measurements. It concerns the transfer of calibration from a reference instrument to another instrument, regardless of the absolute accuracy of the reference.

### 7.2 Noiseless Data:

7.2.1 For clarity, we first consider the case in which the measuring instruments are free of noise. We define vectors  $n$  and  $m$  as: